



## **Manual for TreeSonic Timer**

2020 01 15

## Contents

Introduction .....	1
Package content .....	2
Preparation for the work.....	3
Instead of on/off switch .....	5
Safety .....	6
Maintenance .....	6
Guarantee.....	7
Technical parameters.....	7
Contact.....	8

## Introduction

TreeSonic is designed for tree stiffness prediction, measures the stress wave time between start and stop transducer. The structure of TreeSonic tool is designed by Weyerhaeuser Co. The equipment is patent pending. Patent holder is Weyerhaeuser Co.

## Package content

- TreeSonic display unit
- Start and stop sensors with sliding hammer
- Steel hammer (200 g)
- Rechargeable battery and charger
- User's manual
- Test cables and Voltmeter (optional)



## Preparation for the work

Connect the start sensor to the start connector of the timer. Please see the male and female connector first and use proper orientation while pushing the connector. Finally lock the connector by turning the metal part of the connector clockwise. At this step never touch the black plastic part of the connector. See figure 1.



*Figure 1. While connecting and disconnecting the transducers please touch the metal part only.*

*This is very IMPORTANT!*

*NEVER turn the plastic part of the connector!*

The longer and flat shape transducer is the start and the shorter and cube shape is the stop transducer. Please do not change the transducers.

Drive in the spike of the transducers into the tree you want to test using the sliding hammer. Spike need to penetrate through the bark and stabilize the transducer in the wood material. Please apply 45 degree as spike and fibre angle. See figure 2. Please do not bend the tip while inserting (straight in and avoid the knots) and extracting (straight and completely out) the probes.



*Figure 2. Driving the start (left) and stop (right) transducers into the tree using sliding hammer*

## Instead of on/off switch

There is no on/off switch on the unit. For switching on please hit the **start** transducer, apply a relative strong hit by hammer. Hitting direction is always the axes of the transducer. The first reading is “9999” means that the switching on procedure is successful. The next hit will show the real transit time in microseconds. The unit switches off automatically if no hit on start sensor arrives within 30 seconds. This function saves the battery.

The standard setup is shown on figure 3. The recommended distance between transducers is 1 meter. There is a 1 m mark on the start transducer cable.

Record the readout. Using the average of 3 readouts is recommended. The standard deviation of the readout is less than  $\pm 1.5$  microseconds.




*Figure 3. The recommended setup.*

## Safety

The transducer has sharp spike. Please take care of the spike of the sensor, may injure yourself or person nearby you. When out of use please apply protector tube. Wearing safety shoes, safety glass and gloves is recommended. Fix upper (starter) probe properly, if probe would fall down, never catch while falling. In this case step back, and let it fall down.

## Maintenance

After 10-12 hours operation time, batter goes down. A “BAT LOW” message appears on the screen. Your battery is rechargeable, capacity is 100 mAh. Figure 4. shows how to open the battery compartment.



*Figure 4. The door of the battery compartment can be open by screwdriver (left) or press the door in direction “1” while opening by hand. Change battery when the unit switched off automatically!*

## Guarantee

For the TreeSonic device, including two sensors the guarantee is one year. The guarantee starts at the date displayed on the invoice and valid for the following one year. The repair can be asked from the manufacturer. The guarantee does not concern to the break or deliberate damage of the machine.

## Technical parameters

Dimension of the timer: 36 x 84 x 184 mm

Weight: timer incl. battery: 0,35 kg

hammer incl. handle: 0,25 kg

Start transducer: 1,2 kg

Stop transducer: 1,1 kg

Total: 2,9 kg

Sleeping down time: 30 seconds

Time resolution: 1,2 microsecond

Battery: one piece of 9V block, rechargeable

Capacity: 100 mAh (typical)

Operation time: 10-12 hours

Power requirement: 75 mW

System is water resistant: IP65 protection



## Contact

In case of any questions feel free to contact us:

Email: [office@fakopp.com](mailto:office@fakopp.com)

Web: [www.fakopp.com](http://www.fakopp.com)